



## Return Loss to VSWR Conversion Table

Return Loss (dB)	VSWR	Reflection Coefficient, $\Gamma$	Mismatch Loss (dB)	Reflected Power (%)	Through Power (%)
1	17.39	0.891	6.868	79.43	20.57
2	8.72	0.794	4.329	63.10	36.90
3	5.85	0.708	3.021	50.12	49.88
4	4.42	0.631	2.205	39.81	60.19
5	3.57	0.562	1.651	31.62	68.38
6	3.01	0.501	1.256	25.12	74.88
7	2.61	0.447	0.967	19.95	80.05
8	2.32	0.398	0.749	15.85	84.15
9	2.10	0.355	0.584	12.59	87.41
10	1.92	0.316	0.458	10.00	90.00
11	1.78	0.282	0.359	7.94	92.06
12	1.67	0.251	0.283	6.31	93.69
13	1.58	0.224	0.223	5.01	94.99
14	1.50	0.200	0.176	3.98	96.02
15	1.43	0.178	0.140	3.16	96.84
16	1.38	0.158	0.110	2.51	97.49
17	1.33	0.141	0.088	2.00	98.00
18	1.29	0.126	0.069	1.58	98.42
19	1.25	0.112	0.055	1.26	98.74
20	1.22	0.100	0.044	1.00	99.00
21	1.20	0.089	0.035	0.79	99.21
22	1.17	0.079	0.027	0.63	99.37
23	1.15	0.071	0.022	0.50	99.50
24	1.13	0.063	0.017	0.40	99.60
25	1.12	0.056	0.014	0.32	99.68
26	1.11	0.050	0.011	0.25	99.75
27	1.09	0.045	0.009	0.20	99.80
28	1.08	0.040	0.007	0.16	99.84
29	1.07	0.035	0.005	0.13	99.87
30	1.07	0.032	0.004	0.10	99.90
31	1.06	0.028	0.003	0.08	99.92
32	1.05	0.025	0.003	0.06	99.94
33	1.05	0.022	0.002	0.05	99.95
34	1.04	0.020	0.002	0.04	99.96
35	1.04	0.018	0.001	0.03	99.97
36	1.03	0.016	0.001	0.03	99.97
37	1.03	0.014	0.001	0.02	99.98
38	1.03	0.013	0.001	0.02	99.98
39	1.02	0.011	0.001	0.01	99.99
40	1.02	0.010	0.000	0.01	99.99

$$\Gamma = 10^{(-\text{Return Loss}/20)}$$

$$\text{VSWR} = [1 + 10^{(-\text{Return loss}/20)}] / [1 - 10^{(-\text{Return loss}/20)}]$$

$$\text{VSWR} = (1 + |\Gamma|) / (1 - |\Gamma|)$$

$$\text{Mismatch Loss (dB)} = 10 \log(1 - \Gamma^2)$$

$$\text{Reflected Power (\%)} = 100 * \Gamma^2$$

$$\text{Return Loss (dB)} = -20 \log |\Gamma|$$

$$\text{Return Loss (dB)} = -20 \log [(VSWR-1)/(VSWR+1)]$$

$$\Gamma = (VSWR-1)/(VSWR+1)$$

$$\text{Through Power (\%)} = 100 (1 - \Gamma^2)$$